

Excellent Integrated System Limited

Stocking Distributor

Click to view price, real time Inventory, Delivery & Lifecycle Information:

EPCOS (TDK) B39421R714U310

For any questions, you can email us directly: sales@integrated-circuit.com





SAW Components

Data Sheet R 714







SAW Components	R 714
Resonator	423,22 MHz


Data Sheet

Features

- 1-port resonator
- Provides reliable, fundamental mode, quartz frequency stabilization i.e. in transmitters or local oscillators

Terminals

■ Ni, gold plated



SMD Ceramic package QCC8C

Dimensions in mm, approx. weight 0,1 g

Pin configuration


2	Input
---	-------

6 Output, grounded in 1-port conf.

4,8 Ground (case)

1,3 float

5,7 float / ground



Type	Ordering code	Marking and Package	Packing		
		according to	according to		
R 714	B39431-R 714-U310	C61157-A7-A56	F61074-V8023-Z000		

Electrostatic Sensitive Device (ESD)

Maximum ratings

Operable temperature range	T,	-45/+120	°C	
operation temperature range	·A	10, 1120	_	
Storage temperature range	T .	-45/ + 120	°C.	
Otorage temperature range	'stg	70/1120		
DC voltage	1/	12	\/	between any terminals
DO Voltage	$v_{\rm DC}$	12	v	between any terminals
Source power	P	l 0	dBm	
Source power	1 s	0	ubiii	





SAW Components R 714
Resonator 423,22 MHz

Data Sheet

Characteristics

 $\begin{array}{lll} \mbox{Reference temperature:} & T_{\mbox{A}} = 25 \ ^{\circ} \mbox{C} \\ \mbox{Terminating Source impedance:} & Z_{\mbox{S}} = 50 \ \Omega \\ \mbox{Terminating Load impedance:} & Z_{\mbox{L}} = 50 \ \Omega \\ \end{array}$

		min.	typ.	max.	
Center frequency 1)	f_{c}	423,145	423,22	423,295	MHz
Minimum insertion attenuation	α_{min}	_	1,2	1,9	dB
Unloaded quality factor	Q_U	6000	10000	_	
Ageing of f _c		_	_	±50	ppm
Equivalent circuit elements					
Motional capacitance	C_1	_	2,228	_	fF
Motional inductance	L_1	_	63,47	_	μН
Motional resistance	R_1	_	15	27	Ω
Parallel Capacitance 2)	C_0	_	3,4	_	pF
Temperature coefficient of frequency 3)	TC _f	_	- 0,03	_	ppm/K ²
Turnover temperature	T_0	0	_	30	°C

¹⁾ Center frequency is defined as maximum of the real part of the admittance

 $^{^{2)}}$ If used in two port configuration (pin 2-input, pin 6-output) C_0 is reduced by approx. 0,3 pF.

³⁾Temperature dependence of f_c : $f_c(T_A) = f_c(T_0)(1 + TC_f(T_A - T_0)^2)$





SAW Components R 714
Resonator 423,22 MHz

Data Sheet

Published by EPCOS AG Surface Acoustic Wave Components Division, SAW CE AE PD P.O. Box 80 17 09, D-81617 München

© EPCOS AG 2001. All Rights Reserved.

As far as patents or other rights of third parties are concerned, liability is only assumed for components per se, not for applications, processes and circuits implemented within components or assemblies

The information describes the type of component and shall not be considered as assured characteristics.

Terms of delivery and rights to change design reserved.

For questions on technology, prices and delivery please contact the sales offices of EPCOS AG or the international representatives.

Due to technical requirements components may contain dangerous substances. For information on the type in question please also contact one of our sales offices.