


Excellent Integrated System Limited

Stocking Distributor

Click to view price, real time Inventory, Delivery & Lifecycle Information:

[Zilog](#)
[Z86K1500ZEM](#)

For any questions, you can email us directly:
sales@integrated-circuit.com



CUSTOMER PROCUREMENT SPECIFICATION

Z86K1500ZEM

KEYBOARD FAMILY ICEBOX™ IN-CIRCUIT EMULATOR

FEATURES

■ Supported Devices:

Packages	Emulation ¹
40-Pin DIP	Z86C15/K13/K14/K15/K16/K17/K18

Notes:

1. Programming is not supported.
- ICEBOX Emulator Provides Source-Level Debugging for the Z8 Core.
 - Symbolic Disassembly in the Debug Window

- Selectable Baud Rates – 9600 to 57.6 Kbps
- Windows-Based User Interface
- RS-232C Connector
- HP Logic Analysis System Interface Connector for easy debugging
- Zilog Macro Cross Assembler (ZMASM)
 - Structured Assembly and Data Code
 - Source-Level Debug Support
 - Built-In Register Equates
 - Linker

GENERAL DESCRIPTION

Zilog's ICEBOX™ in-circuit emulators are interactive, Windows-oriented development tools providing a real-time environment for developing and debugging software. Also included is a full-featured macro cross assembler to enhance programmer productivity when used in conjunction with the Z86K15 ICEBOX Emulator.

The ICEBOX provides a hardware platform that is a significant improvement compared to software simulators. The ICEBOX is faster in operation, making it more practical than software simulators for code development.

The Z86K15 ICEBOX Emulator, which supports the Z86K15 family and Z86C15 family of keyboard devices listed above, provides essential timing and I/O circuitry to simplify user emulation of the prototype hardware and software product.

The Z86K15 ICEBOX Emulator can be connected to a serial port (COM1, COM2, COM3, and COM4) of the host computer, and it uses Graphical User Interface (GUI) software.

HARDWARE SPECIFICATIONS

Operating Conditions

Operating Temperature:	20°C
±10°C	
Emulation Speed:	
Internal SCLK (minimum)	4 MHz
Internal SCLK (maximum)	6 MHz
Operating Humidity:	10-90%
RH (non-condensing)	

Power Requirements

+4.75 VDC to +5.25 VDC
(+5.0 VDC @ 0.5A typical; max. is 0.75A)

Dimensions

2.5 in. H x 6.25 in. W x 9.5 in D

Serial Interface

RS-232C @ 9600, 19200 (default), 28800, or 57600 Baud

Emulation Memory

Z8 = 32 KB (maximum)

Hardware Breakpoints

Z8 = 32K (maximum)

HOST COMPUTER

Minimum Requirements

IBM PC (or 100-percent compatible) 386-Based Machine
33 MHz
4 MB RAM
VGA Video Adapter
Hard Disk Drive (3.0 MB free space)
3.5-inch, High-Density (HD) Floppy Disk Drive
RS-232C COM Port
Mouse or Pointing Device
Microsoft Windows 3.1

Recommended:

The following changes to the Minimum Requirements are recommended for increased performance:
486- or Pentium-Based Machine
66 MHz (or faster)
8 MB of RAM (or more)
SVGA Video Adapter
Color Monitor
Printer
Windows 95

Zilog

KIT CONTENTS

Qty.	Item
1	Z86K15 ICEBOX Emulator

Cables/Pods

1	40-Pin DIP Z86K15 Pod and Cable
1	40-Pin DIP C15 Pod
1	Power Cable
1	RS-232C Serial Cable, DB25 M-F

Host Software

Z8 GUI Diskette
Zilog Macro Cross Assembler Diskette

Documentation

The Z86K15 ICEBOX™ Emulator User's Manual

Zilog Macro Cross Assembler User's Manual

Software License and Limited Warranty Agreement

Registration Card (2)

Additional Required Items Not Supplied with the Support Package

A source of power (+4.75 VDC to +5.25 VDC Max [+5.0 VDC typical]) for the emulator. This can be a laboratory power supply with supply current of 0.75A or more.

Your Target Design

Typically, this is a wire-wrapped or printed-circuit prototype that includes a socket for the target device, into which you can plug the emulation cable from the emulator.

Optional Items Not Supplied with the This Package

25-Pin to 9-Pin RS-232 adapter

HP Logic Analyzer Kit (Z89C0000ZHP or ZINVASM0ZHP)

© 1997 by Zilog, Inc. All rights reserved. No part of this document may be copied or reproduced in any form or by any means without the prior written consent of Zilog, Inc. The information in this document is subject to change without notice. Devices sold by Zilog, Inc. are covered by warranty and patent indemnification provisions appearing in Zilog, Inc. Terms and Conditions of Sale only. Zilog, Inc. makes no warranty, express, statutory, implied or by description, regarding the information set forth herein or regarding the freedom of the described devices from intellectual property infringement. Zilog, Inc. makes no warranty of merchantability or fitness for any purpose. Zilog, Inc. shall not be responsible for any errors that may appear in this document. Zilog, Inc. makes no commitment to update or keep current the information contained in this document.

The software described herein will be provided on an "as is" basis and without warranty. Zilog accepts no liability for incidental or consequential damages arising from use of the software.

Zilog's products are not authorized for use as critical components in life support devices or systems unless a specific written agreement pertaining to such intended use is executed between the customer and Zilog prior to use. Life support devices or systems are those which are intended for surgical implantation into the body, or which sustains life whose failure to perform, when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the user.

Zilog, Inc. 210 East Hacienda Ave.
Campbell, CA 95008-6600
Telephone (408) 370-8000
FAX 408 370-8056
Internet: <http://www.zilog.com>