

Excellent Integrated System Limited

Stocking Distributor

Click to view price, real time Inventory, Delivery & Lifecycle Information:

Murata Electronics North America BLM18RK471SN1D

For any questions, you can email us directly: sales@integrated-circuit.com

Datasheet of BLM18RK471SN1D - FERRITE CHIP 470 OHM 200MA 0603 Contact us: sales@integrated-circuit.com Website: www.integrated-circuit.com

Chip Ferrite Bead

Part Numbering

(Part Number)

| ١ | BL | M | 18 | AG | 102 | S | N | 1 | D |
|---|----|---|----|----|-----|---|---|---|---|
| | _ | _ | _ | _ | _ | _ | _ | _ | _ |

Product ID

| Product ID | |
|------------|--------------------|
| BL | Chip Ferrite Beads |

2Type

| C 7/2 - | | |
|---------|---------------------------------------|--|
| Code | Туре | |
| Α | Array Type | |
| E | DC Bias Characteristics Improved Type | |
| M | Ferrite Bead Single Type | |

3Dimensions (LXW)

| 3 2 | | |
|------------|------------------|-------|
| Code | Dimensions (L×W) | EIA |
| 02 | 0.4×0.2mm | 01005 |
| 03 | 0.6×0.3mm | 0201 |
| 15 | 1.0×0.5mm | 0402 |
| 18 | 1.6×0.8mm | 0603 |
| 2A | 2.0×1.0mm | 0804 |
| 21 | 2.0×1.25mm | 0805 |
| 31 | 3.2×1.6mm | 1206 |
| 32 | 3.2×2.5mm | 1210 |
| 41 | 4.5×1.6mm | 1806 |

6 Impedance

Expressed by three figures. The unit is in ohm (Ω) at 100MHz. The first and second figures are significant digits, and the third figure expresses the number of zeros that follow the two figures.

6Electrode

Expressed by a letter.

| Ex.) | Code | Electrode |
|------|------|------------|
| | S/T | Sn Plating |
| | Α | Au Plating |

Category

| Code | Category | | |
|------|----------------|-----------------------------------|--|
| N | For General | | |
| Z | For Automotive | e Infotainment Powertrain, Safety | |
| Н | For Automotive | | |

8 Number of Circuits

| Code | Number of Circuits |
|------|--------------------|
| 1 | 1 Circuit |
| 4 | 4 Circuits |

4 Characteristics/Applications

| Code *1 | Characteristics/Applications | Series |
|---------|--|--------------------------|
| AG | | BLM03/15/18/21, BLA2A/31 |
| AX | For General Use | BLM02/03/15 |
| TG | | BLM18 |
| ВА | | BLM15/18 |
| ВВ | | BLM03/15/18/21, BLA2A |
| ВС | For High-speed Signal Lines | ines BLM03/15 |
| BD | | BLM03/15/18/21, BLA2A/31 |
| вх | | BLM02/15 |
| PD | | BLM15 |
| PG | For Power Lines | BLM03/15/18/21/31/41 |
| PN | For Fower Lines | BLE32 |
| PX | | BLM03/15 |
| KG | For Power Lines (Low DC Resistance Type) | BLM18 |
| SG | Tot Tower Lines (Low Do Hesistance Type) | DEWIG |
| RK | For Digital Interface | BLM18/21 |
| HG | For GHz Band General Use | BLM03/15/18 |
| EB | For GHz Band High-speed Signal Lines (Low Direct Current Type) | BLM03 |
| EG | For GHz Band General Use (Low DC Resistance Type) | BLM15/18 |
| НВ | | BLM03/15/18 |
| HD | For GHz Band High-speed Signal Lines | BLM03/15/18 |
| HE | | BLM18 |
| нк | For GHz Band Digital Interface | BLM18 |
| GA | For High-GHz Band High-speed Signal Lines | BLM15 |
| GG | For High-GHz Band General Use | BLM15/18 |

^{*1} Frequency characteristics vary with each code.



Distributor of Murata Electronics North America: Excellent Integrated System Limited

Datasheet of BLM18RK471SN1D - FERRITE CHIP 470 OHM 200MA 0603 Contact us: sales@integrated-circuit.com Website: www.integrated-circuit.com

BL Chip Ferrite Bead Part Numbering

Packaging

| Code | Packaging | Series |
|------|-------------------------------|--------------------------------|
| K | Embossed Taping (ø330mm Reel) | BLE, BLM21*1/31/41 |
| L | Embossed Taping (ø180mm Reel) | DLE, DLMZ1 /31/41 |
| В | Bulk | All Series |
| J | Paper Taping (ø330mm Reel) | BLM03/15/18*3/21*2, BLA2A/31 |
| D | Paper Taping (ø180mm Reel) | BLM02/03/15/18/21 *2, BLA2A/31 |

^{*1} BLM21BD222SN1/BLM21BD272SN1 only. *2 Except for BLM21BD222SN1/BLM21BD272SN1

^{*3} Except for BLM18T