

Excellent Integrated System Limited

Stocking Distributor

Click to view price, real time Inventory, Delivery & Lifecycle Information:

[Phyton Inc.](#)
[AE-Q32-AV1](#)

For any questions, you can email us directly:
sales@integrated-circuit.com

AE-Q32-AV1



DIP28/QFP32 specialized adapter for Atmel microcontrollers.

Device package dimensions: body - 7.0 x 7.0 x 1.2 mm, body with pins - 9.0 x 9.0 mm, 0.8 mm pitch.

Click the programmer model below to get an appropriate list of the devices supported by the adapter:

- [ChipProg+](#)
- [ChipProg-40](#)
- [ChipProg-48, ChipProg-G4](#)

Adapter analogues supplied by third-party vendors:

Logical Systems: PA32Q1498-28D6-20

Adapter Wiring Diagram:

DIP28	TQFP-32
1	29
2	30
3	31
4	32
5	1
6	2
7	4,6
8	3,5
9	7
10	8
11	9
12	10

13	11
14	12
15	13
16	14
17	15
18	16
19	17
20	18
21	20
22	21
23	23
24	24
25	25
26	26
27	27
28	28