

Excellent Integrated System Limited

Stocking Distributor

Click to view price, real time Inventory, Delivery & Lifecycle Information:

[Phyton Inc.](#)
[AE-TS32W](#)

For any questions, you can email us directly:
sales@integrated-circuit.com

AE-TS32W



DIP32/TSOP32 specialized adapter for Flash memory.
Device package dimensions: 8 x 20 mm, 0.5 mm pitch.

Click the programmer model below to get an appropriate list of the devices supported by the adapter:

- [ChipProg+](#)
- [ChipProg-40](#)
- [ChipProg-48, ChipProg-G4](#)

Adapter analogues supplied by third-party vendors:

Logical Systems: PA32TS20-OT

Adapter Wiring Diagram:

DIP-32	TSOP-32
1	9
2	10
3	11
4	12
5	13
6	14
7	15
8	16
9	17
10	18
11	19
12	20

13	21
14	22
15	23
16	24
17	25
18	26
19	27
20	28
21	29
22	30
23	31
24	32
25	1
26	2
27	3
28	4
29	5
30	6
31	7
32	8