

## Excellent Integrated System Limited

Stocking Distributor

Click to view price, real time Inventory, Delivery & Lifecycle Information:

[Phyton Inc.](#)  
[AE-TS48-NAND-2](#)

For any questions, you can email us directly:  
[sales@integrated-circuit.com](mailto:sales@integrated-circuit.com)

## AE-TS48-NAND-2



DIP40/TSOP48 specialized adapter for NAND Flash devices.  
 Device package dimensions: 12 x 20 mm, 0.5 mm pitch.

Click the programmer model below to get an appropriate list of the devices supported by the adapter:

- [ChipProg+](#)
- [ChipProg-40](#)
- [ChipProg-48, ChipProg-G4](#)

### Adapter Wiring Diagram:

DIP-40	TSOP-48	74AHC14	C1, 0.1 uF
1	35		
2			
3			
4	4		
5	5		
6	6		
7	7		
8		1	
	8	4	
9	9		
10	10		
11	14		
12	15		
13			

14			
15	20		
16	16		
17	17		
18		13	
	18	10	
19	19		
20	13,25,36,48	7	1
21	26		
22	27		
23	28		
24	29		
25	30		
26	31		
27	32		
28	33		
29	40		
30	41		
31	42		
32	43		
33	44		
34	45		
35	46		
36	47		
37			
38			
39	38		
40	12,37	14	2
		2,3	
		11,12	