

Excellent Integrated System Limited

Stocking Distributor

Click to view price, real time Inventory, Delivery & Lifecycle Information:

[Texas Instruments](#)
[TXS02326AMRGER](#)

For any questions, you can email us directly:

sales@integrated-circuit.com



TXS02326A

www.ti.com


SCES830A –MAY 2012–REVISED AUGUST 2013

DUAL-SUPPLY 2:1 SIM CARD MULTIPLEXER/TRANSLATOR WITH AUTOMATIC DETECTION AND SLOT DEDICATED DUAL LDO

Check for Samples: [TXS02326A](#)

FEATURES

- **Level Translator**
 - VDDIO Range of 1.7-V to 3.3-V
- **Low-Dropout (LDO) Regulator**
 - 50-mA LDO Regulator With Enable
 - 1.8-V or 2.95-V Selectable Output Voltage
 - 2.3-V to 5.5-V Input Voltage Range
 - Very Low Dropout: 100 mV (Max) at 50 mA
- **Control and Communication Through I²C Interface With Baseband Processor**
- **ESD Protection Exceeds JESD 22**
 - 2500-V Human-Body Model (A114-B)
 - 6000-V Human-Body Model (A114-B) on VSIM1, SIM1CLK, SIM1I/O, SIM1RST, VSIM2, SIM2CLK, SIM2I/O, SIM2RST
 - 1000-V Charged-Device Model (C101)
- **Package**
 - 24-Pin QFN (4 mm x 4 mm)



Note: The Exposed Thermal Pad must be connect to Ground.

DESCRIPTION/ORDERING INFORMATION

The TXS02326A is a complete dual-supply standby Smart Identity Module (SIM) card solution for interfacing wireless baseband processors with two individual SIM subscriber cards to store data for mobile handset applications. It is a custom device which is used to extend a single SIM/UICC interface to support two SIMs/UICCs.

The device complies with ISO/IEC Smart-Card Interface requirements as well as GSM and 3G mobile standards. It includes a high-speed level translator capable of supporting Class-B (2.95-V) and Class-C (1.8-V) interfaces; two low-dropout (LDO) voltage regulators with output voltages that are selectable between 2.95-V Class-B and 1.8-V Class-C interfaces; an integrated "fast-mode" 400 kb/s "slave" I²C control register interface, for configuration purposes; and a 32-kHz clock input, for internal timing generation. The TXS02326A also includes a shutdown input and a comparator input that detects battery pack removal to safely power-down the two SIM cards. The shutdown input and comparator input are equipped with two programmable debounce counter (i.e. BSI input and SDN input) circuits realized by an 8 bit counter.

The voltage-level translator has two supply voltage pins. VDDIO sets the reference for the baseband interface and can be operated from 1.7-V to 3.3-V. VSIM1 and VSIM2 are programmed to either 1.8-V or 2.95-V, each supplied by an independent internal LDO regulator. The integrated LDO accepts input battery voltages from 2.3-V to 5.5-V and outputs up to 50 mA to the B-side circuitry and external Class-B or Class-C SIM card.

ORDERING INFORMATION

For the most current package and ordering information, see the Package Option Addendum at the end of this document.



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

PRODUCTION DATA information is current as of publication date. Products conform to specifications per the terms of the Texas Instruments standard warranty. Production processing does not necessarily include testing of all parameters.

Copyright © 2012–2013, Texas Instruments Incorporated

SCES830A –MAY 2012–REVISED AUGUST 2013

www.ti.com



This integrated circuit can be damaged by ESD. Texas Instruments recommends that all integrated circuits be handled with appropriate precautions. Failure to observe proper handling and installation procedures can cause damage.

ESD damage can range from subtle performance degradation to complete device failure. Precision integrated circuits may be more susceptible to damage because very small parametric changes could cause the device not to meet its published specifications.




Figure 1. Interfacing With SIM Card

TERMINAL FUNCTIONS

| NO. | NAME | TYPE ⁽¹⁾ | POWER DOMAIN | DESCRIPTION |
|-----|---------|---------------------|--------------|--|
| 1 | IRQ | I/O | VDDIO | Interrupt to baseband. This signal is used to set the I2C address. |
| 2 | RSTX | I | VDDIO | Active-low reset input from baseband |
| 3 | SDN | I | VDDIO | Power down SIM2; for example, from switch |
| 4 | BSI | I | VDDIO | Analog signal from battery. This input accepts input voltages up to 3 V. |
| 5 | SIM2CLK | O | VSIM2 | SIM2 clock |
| 6 | SIM2I/O | I/O | VSIM2 | SIM2 data |
| 7 | SIM2RST | O | VSIM2 | SIM2 reset |
| 8 | VSIM2 | O | VSIM2 | 1.8 V/2.95 V supply voltage to SIM2 |
| 9 | VBAT | P | VBAT | Battery power supply |
| 10 | GND | G | | Ground |
| 11 | VSIM1 | O | VSIM1 | 1.8 V/2.95 V supply voltage to SIM1 |
| 12 | SIM1RST | O | VSIM1 | SIM1 reset |
| 13 | SIM1I/O | I/O | VSIM1 | SIM1 data |
| 14 | SIM1CLK | O | VSIM1 | SIM1 clock |
| 15 | NC | | | No connect |
| 16 | SIMRST | I | VDDIO | UICC/SIM reset from baseband |
| 17 | SIMCLK | I | VDDIO | UICC/SIM clock |
| 18 | SIMI/O | I/O | VDDIO | UICC/SIM data |
| 19 | OE | I | VDDIO | UICC/SIM data direction from baseband |
| 20 | GND | G | | |
| 21 | VDDIO | P | VDDIO | 1.8-V power supply for device operation and I/O buffers toward baseband |
| 22 | CLK | I | VDDIO | 32-kHz clock |
| 23 | SCK | I | VDDIO | I ² C clock |
| 24 | SDA | I/O | VDDIO | I ² C data |

(1) G = Ground, I = Input, O = Output, P = Power

Table 1. Register Overview

| REGISTER BITS | | | | | | | | COMMAND BYTE (HEX) | REGISTER | READ OR WRITE | POWER-UP DEFAULT |
|--------------------------------|----------------------------|------------------------------|--------------------------------|----------------------------------|--|------------------------------|----------------------------|--------------------------|--------------------------------------|---------------------|---------------------|
| B7 | B6 | B5 | B4 | B3 | B2 | B1 | B0 | | | | |
| 0 | 0 | 0 | 1 | 0 | 0 | 1 | 0 | 00h | Device hardware revision information | R | 0001 0010 |
| 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 01h | Software revision information | R | 0000 0000 |
| SIM2 Interface Status | | SIM1 Interface Status | | Battery Removal Interrupt Status | Battery Status | SDN Interrupt Status | SDN Status | 04h | Status Register | R | 0000 0000 |
| SIM2 Interface Status | | SIM2 Voltage Select | SIM2 LDO Enable/Disable | SIM1 Interface Status | | SIM1 Voltage Select | SIM1 LDO Enable/Disable | 08h | SIM Interface Control Register | R/W | 0000 0000 |
| BSI Debounce Counter Value | | | | | | | | 0Ah | BSI Input Debounce Counter | R/W | 0000 0100 |
| SDN Debounce Counter Value | | | | | | | | 0Bh | SDN Input Debounce Counter | R/W | 0000 0100 |
| Reserved / Not Supported | | | | | | | | 0Ch | Reserved | R/W | 0000 0000 |
| Clock Source Select | Clock Control (Reserved) | | | | | | | 0Dh | External Clock Control | R/W | 0000 0000 |
| SDN Detection Behavior control | SDN Level Detection Select | SDN Interrupt Enable/Disable | BSI Detection Behavior Control | BSI Level Detection Select | Battery Removal Interrupt Enable/Disable | OE Direction Control | OE Control Select | 0Eh | Device Control Register | R/W | 0000 0000 |
| | | | | | | | | 10h-14h | Device-specific testing | R/W | xxxx xxxx |
| Reserved | | | | | | SDN Pull-down Enable/Disable | SDN Pull-up Enable/Disable | 15h | General purpose | R/W | 0000 0000 |

Table 2. Device Hardware Revision Register (00h)

| Device HW Driver Register | Bits(s) | Type (R/W) | Description |
|---------------------------|---------|------------|--|
| HW identification | 7:0 | R | This register contains the manufacturer and device ID ⁽¹⁾ (value to be specified by the manufacturer) |

- (1) The manufacturer ID part of this data shall remain unchanged when the HW revision ID is updated. The manufacturer ID shall uniquely identify the manufacturer. The manufacturer ID is encoded on the MSB nibble.

Table 3. Device Software Revision Register (01h)

| Device SW Driver Register | Bits(s) | Type (R/W) | Description |
|---------------------------|---------|------------|---|
| SW Driver Version | 7:0 | R | This register contains information about the SW driver required for this device. This information shall only be updated when changes to the device requires SW modifications. Initial register value is 00h |

Table 4. Status Register (04h)

| Status Register | Bits(s) | Type (R/W) | Description |
|-----------------------------|--------------------|------------|---|
| SDN Status | 0 | R | SDN signal state captured at the input pin '0' SDN signal at GND '1' SDN signal at VDDIO level |
| SDN Interrupt | 1 | R | SDN interrupt status '0' No interrupt '1' Interrupt occurred, (the read operation will automatically clear this bit) |
| Battery Status | 2 | R | '0' Battery present '1' Battery not present, i.e. debounce counter expired |
| Battery Removal Interrupt | 3 | R | Battery removal interrupt status '0' No interrupt '1' Interrupt occurred, (the read operation will automatically clear this bit) |
| SIM1 Interface Status [1:0] | 5:4 ⁽¹⁾ | R | Status of SIM1 interface '00' Powered down with pull-downs activated '01' Isolated with pull-downs deactivated '10' Powered with pull downs activated '11' Active with pull downs deactivated |
| SIM2 Interface Status [1:0] | 7:6 ⁽¹⁾ | R | Status of SIM2 interface '00' Powered down with pull-downs activated '01' Isolated with pull-downs deactivated '10' Powered with pull downs activated '11' Active with pull downs deactivated |

- (1) The content of bits 5:4 and 7:6 reflects the value written to the state bits in the SIM Interface control register 3:2 and 7:6 respectively and the setting of the regulator bits in the SIM interface control register 0 and 4 respectively.

Table 5. State and Status Bit Mapping

| SIM Interface Control Register (08h) SIM1 interface state bits 3:2 SIM2 interface state bits 7:6 | SIM Interface Control Register (08h) SIM1 regulator control bit 0 SIM2 regulator control bit 4 | SIM Status Register (04h) SIM1 status bits 5:4 SIM2 status bits 7:6 | Comment |
|--|--|---|---|
| '00' Powered down state with pull-downs activated | '0' Regulator is off, regulator output is pulled down | '00' Powered down with pulldowns activated | |
| '00' Powered down state with pull-downs activated | '1' Regulator is powered on, regulator output pull-down is released | '10' Powered with totem pole pull-downs | |
| '01' Isolated state with pulldowns deactivated | '0' Regulator is off, regulator output is pulled down | '00' Powered down with pulldowns activated | The interface can only be in isolated state when the interface is powered |
| '01' Isolated state with pulldowns deactivated | '1' Regulator is powered on, regulator output pull-down is released | '01' Isolated with pull-downs deactivated | |
| '10' Not allowed | '0' Regulator is off, regulator output is pulled down | '00' Powered down with pulldowns activated | This combination shall not be used. If used the status bit coding is as specified |

Table 5. State and Status Bit Mapping (continued)

| SIM Interface Control Register (08h) SIM1 interface state bits 3:2 SIM2 interface state bits 7:6 | SIM Interface Control Register (08h) SIM1 regulator control bit 0 SIM2 regulator control bit 4 | SIM Status Register (04h) SIM1 status bits 5:4 SIM2 status bits 7:6 | Comment |
|--|--|---|---|
| '10' Not allowed | '1' Regulator is powered on, regulator output pull-down is released | '10' Powered with pull downs activated | This combination shall not be used. If used the status bit coding is as specified |
| '11' Active state with pull-downs deactivated | '0' Regulator is off, regulator output is pulled down | '00' Powered down with pulldowns activated | The interface can only be active if it is powered |
| '11' Active state with pull-downs deactivated | '1' Regulator is powered on, regulator output pull-down is released | '11' Active with pull-downs deactivated | |

Table 6. SIM Interface Control Register (08h)^{(1) (2)}

| Status Register | Bit(s) | Type (R/W) | Description |
|----------------------------------|--------|------------|---|
| SIM1 Regulator Control | 0 | R/W | '0' Regulator is off, regulator output is pulled down '1' Regulator is powered on, regulator output pull-down is released |
| SIM1 Regulator Voltage Selection | 1 | R/W | '0' 1.8 V '1' 2.95 V |
| SIM1 Interface State [1:0] | 3:2 | R/W | Status of SIM1 interface |
| | | | '00' state is dependent on bit 0: If bit 0 = '0', then powered down state with pull-downs activated If bit 0 = '1', then isolated state with pull-downs deactivated |
| | | | Pull down resistor active Totem pole pull down |
| | | | '01' Isolated state with pull-downs deactivated Output latched at previous state driven by totem pole output |
| | | | '10' Not allowed Not allowed |
| SIM2 Interface State [1:0] | 7:6 | R/W | '11' Active state with pull-downs deactivated Outputs follow the inputs |
| | | | Status of SIM2 interface |
| | | | '00' State is dependent on bit 4: If bit 4 = '0', then powered down state with pull-downs activated If bit 4 = '1', then isolated state with pull-downs deactivated |
| | | | Pull down resistor active Totem pole pull down |
| | | | '01' Isolated state with pull-downs deactivated Output latched at previous state driven by totem pole output |
| SIM2 Interface State [1:0] | 7:6 | R/W | '10' Not allowed Not allowed |
| | | | '11' Active state with pull-downs deactivated Outputs follow the inputs |

(1) Reset value: 00h

(2) The state '10', on bits 3:2 and 7:6, is not prevented by HW but shall never be set by SW. State '10' means that the interface is powered with the pull-downs active, this state correspond to state '00' with the regulator being switched on. Setting the state to '10' does not have any impact on the corresponding regulator bit setting. The regulator control bits do not impact the state bits in this register. The regulator control bits however do impact the status bits in the status register.

Table 7. Battery Presence Detection Debounce Counter (0Ah)⁽¹⁾ (2)

| BSI Debounce Counter | Bits(s) | Type (R/W) | Description |
|------------------------------|---------|------------|--|
| Debounce Counter Value [7:0] | 7:0 | R/W | This register contains the BSI input debounce counter value. The value 00h means that the counter is not used, i.e. no debounce. |

(1) Reset value: 04h

(2) Updating the register causes the counter to restart with the new value if the counter is counting when the register is updated. The new value shall take affect no later than one clock cycle (32 KHz) after the register has been updated.

Table 8. SDN Input Debounce Counter (0Bh)⁽¹⁾ (2)

| SDN Debounce Counter | Bits(s) | Type (R/W) | Description |
|------------------------------|---------|------------|--|
| Debounce Counter Value [7:0] | 7:0 | R/W | This register contains the SDN input debounce counter value. The value 00h means that the counter is not used, i.e. no debounce. |

(1) Reset value: 04h

(2) Updating the register causes the counter to restart with the new value if the counter is counting when the register is updated. The new value shall take affect no later than one clock cycle (32 KHz) after the register has been updated.

Table 9. External Clock Control (0Dh)⁽¹⁾

| Clock Control Register | Bits(s) | Type (R/W) | Description |
|------------------------|---------|------------|---|
| Clock Control | 6:0 | R/W | Reserved |
| Clock Source Select | 7 | R/W | '0' Internal clock source used '1' External clock source CLK (supplied on pin 22 used) |

(1) Reset value: 00h

Table 10. Device Control Register (0Eh)⁽¹⁾

| Clock Control Register | Bits(s) | Type (R/W) | Description |
|---------------------------|---------|------------|--|
| OE Control | 0 | R/W | '0' OE is not used to control the data direction on the selected SIM I/O and the base band I/O '1' OE controls the data direction, see below |
| OE Direction Control | 1 | R/W | '0' OE input = '0' data direction Base band -> SIM OE input = '1' data direction SIM -> base band '1' OE input = '0' data direction SIM -> base band OE input = '1' data direction Base band -> SIM |
| Battery Removal Interrupt | 2 | R/W | '0' Battery removal interrupt disabled '1' Battery removal detected causes interrupt on IRQ (interrupt sets b3 in the status register) |
| BSI Level Detection | 3 | R/W | BSI detection level '0' 1.2V '1' 1.65V |
| BSI Detection Control | 4 | R/W | BSI detection behavior '0' Battery not present causes automatic power down of both SIM interfaces '1' Battery not present doesn't cause automatic power down |
| SDN Detection Interrupt | 5 | R/W | '0' SDN detection interrupt disabled '1' SDN detected causes interrupt on IRQ (interrupt sets b1 in the status register) |
| SDN Detection Level | 6 | R/W | SDN input active level '0' SDN is active low i.e. automatic shutdown occurs when debounced SDN is low. '1' SDN is active high i.e. automatic shutdown occurs when debounced SDN is high |
| SDN Detection Control | 7 | R/W | Disable automatic power down upon SDN detection '0' SDN detection causes automatic power down of SIM2 interface '1' SDN detection doesn't cause automatic power down of SIM2 interface |

(1) Reset value: 00h

Table 11. General Purpose Register (15h)⁽¹⁾

| Function | Bit(s) | Type (R/W) | Description |
|-----------------------|--------|------------|---|
| SDN pull-up control | 0 | R/W | '0' SDN input pull-up enabled '1' SDN input pull-up disabled |
| SDN pull-down control | 1 | R/W | '0' SDN pull-down disabled '1' SDN pull-down enabled |
| RFU | 7:2 | R/W | |

(1) The RFU bits shall allow for the write operation to complete but shall read as '0'. The SW should write '0' into these locations, reset value.




BASIC DEVICE OPERATION

The TXS02326A is controlled through a standard I²C interface reference to VDDIO. It is connected between the two SIM card slots and the SIM/UICC interface of the baseband. The device uses VBAT and VDDI/O as supply voltages. The supply voltage for each SIM card is generated by an on-chip low drop out regulator. The interface between the baseband and the TXS02326A is reference to VDDIO while the interface between the TXS02326A and the SIM card is referenced to the LDO output of either VSIM1 or VSIM2 depending on which slot is being selected. The VDDIO on the baseband side normally does not exceed 1.8V, thus voltage level shifting is needed to support a 3V SIM/UICC interface (Class B).

The TXS02326A has two basic states, the reset and operation state. The baseband utilizes information in the status registers to determine how to manipulate the control registers to properly switch between two SIM cards. These fundamental sequences are outlined below and are to help the user to successfully incorporate this device into the system.

DEVICE ADDRESS

The address of the device is shown below:



Address Reference

| IRQ@ Reset | R/W | Slave Address |
|------------|-------|----------------------|
| 0 | 0 (W) | 120 (decimal), 78(h) |
| 0 | 1 (R) | 121 (decimal), 79(h) |
| 1 | 0 (W) | 122 (decimal), 7A(h) |
| 1 | 1 (R) | 123 (decimal), 7B(h) |

RESET STATE

In the reset state the device settings are brought back to their default values and any SIM card that has been active is deactivated. After reset, neither of the UICC/SIM interfaces is selected. The active pull-downs at the UICC/SIM interface are automatically activated. To ensure the system powers up in an operational state, device uses an internal 32 KHz clock for internal timing generation. After power up, the system has the option to continue to utilize the internal clock or select an external clock source. This clock source is selectable by the Clock Source Select I²C register bit.

- Power up the TXS02326A by asserting VBAT to enter the operation state
- I²C Interface becomes active with the VDD_I/O supply

RESET summary:

- Any pending interrupts are cleared
- I²C registers are in the default state
- BSI and SDN counter value in the registers are set to four clock cycles or "0000 0100"
- Both on chip regulators are set to 1.8V and disabled
- All SIM1 and SIM2 signals are pulled to GND

SETTING UP THE SIM INTERFACE

The TXS02326A supports both Class C (1.8V) or Class B (2.95V) SIM cards. In order to support these cards types, the interface on the SIM side needs to be properly setup. After power up, the system should default to SIM1 card. The following sequence outlines a rudimentary sequence of preparing the SIM1 card interface:

- Configure the SIM1 regulator to 1.8V by asserting B1 = 0 in the SIM Interface Control Register (08h). The system by default should start in 1.8V mode.
- Configure the OE signal by asserting B0 = 0 in the Device Control Register (0Eh). The default value essentially disables the OE pin and the device is configured as an auto direction translator.
- The baseband SIM interface is set to a LOW state.
- Disable the SIM1 interface by asserting B2 = 0 and B3 = 0 in the SIM Interface Control Register.
- Disable the SIM2 interface by asserting B6 = 0 and B7 = 0 in the SIM Interface Control Register.
- VSIM1 voltage regulator should now be activated by asserting B0 = 1 in the SIM Interface Control Register.
- Enable the SIM1 interface by asserting B2 = 1 and B3 = 1 in the SIM Interface Control Register.
- The SIM1 interface (VSIM1, SIM1CLK, SIM1I/O) is now active. The TXS02326A relies on the baseband to perform the power up sequencing of the SIM card. If there is lack of communication between the baseband and the SIM card, the SIM1 interface must be powered-down and then powered up again through the regulator by configuring it to 2.95V by asserting B1 = 1 in the SIM Interface Control Register.

SWITCHING BETWEEN SIM CARDS

The following sequence outlines a rudimentary sequence of switching between the SIM1 card and SIM2 card:

- Put the SIM1 card interface into “clock stop” mode then assert B2 = 1 and B3 = 0 in the SIM Interface Control Register (08h). This will latch the state of the SIM1 interface (SIM1CLK, SIM1I/O, SIM1RST).
- There can be two scenarios when switching to SIM2 card:
 - SIM2 may be in the power off mode, B6 = 0 and B7 = 0 in the Status Register (04h). If SIM2 is in power off mode, the SIM/UICC interface will need to be set to the power off state. In this case the baseband will most likely need to go through a power up sequence iteration
 - SIM2 may already be in the “clock stop” mode, B6 = 1 and B7 = 0 in the Status Register (04h). If SIM2 is in “clock stop” mode, the interface between the baseband and the device is set to the clock stop mode levels that correspond to the SIM2 card interface.
- After determining whether the SIM2 card is either in power off mode or clock stop mode, the SIM2 card interface is then activated by asserting B6 = 1 and B7 = 1 in the SIM Interface Control Register (08h) and the negotiation between the baseband and card can continue.
- Switching from SIM2 to SIM1 done in the same manner.

AUTOMATIC SHUTDOWN

Both SIM card interfaces can be configured to automatically shut down upon disconnecting the battery. The shutdown threshold $BSI_{Threshold}$ is configured in B3 of the Device Control Register (0Eh). Two threshold levels are available for this configuration. When the BSI input level exceeds the $BSI_{Threshold}$ level that caused this power-down, both SIM card interfaces will automatically be shut down. If the battery removal interrupt is enabled through B2 of the Device Control Register, then an interrupt will be issued to the baseband on IRQ. This case may happen if the user decides to remove the battery.

There are two scenarios for shutting down each SIM: SIMx is “active”, or in “clock stop” mode. In clock stop mode, when the debounce timer expires, the SIMx signals all go low immediately, then the regulator is disabled one 32KHz cycle later. If SIMx is active, the signals go low and the regulator is disabled in a particular sequence to be described in the next section.

The SIM2 interface can also be configured to automatically shut down via the SDN pin.



BSI / SDN DEBOUNCE AND AUTOMATIC SHUTDOWN SEQUENCE TIMING

There are two debounce counters: one each for the BSI and SDN inputs. For each counter, when the device is reset or the related input is “false”, the counter is loaded with the value in the associated Debounce Counter register and the debounced signal (i.e. BSI_DEB or SDN_DEB) is subsequently set to a “false” state. When the related input becomes “true”, the counter begins counting down on subsequent CLK rising-edges. (CLK is either the internal or external 32 kHz clock as selected by Clock Source Select)

If the input changes state during the count, the counter is again loaded with the register value. The debounce counter propagates the input signal to the output when the counter expires.

For BSI and BSI_DEB, the “true” state is high. For SDN and SDN_DEB, the “true” state is the state stored in the SDN Detection Level register. Once either count reaches zero, the debounced signal switches to the “true” state on the next CLK rising edge. Writing a new value to the SDN detection level register such that SDN is now in the TRUE state will force the debounce counter to zero, but will not generate an interrupt nor initiate a shutdown sequence.

If BSI_DEB goes high and Battery Removal Interrupt (bit 2 of the Device Control Register) is 1, an interrupt is generated and appears on IRQ. Also, if BSI_DEB goes high and BSI Detection Control (bit 4 of the Device Control Register) is 0, the Automatic Shutdown sequence begins for both SIM’s.

If SDN_DEB goes “true” and SDN Detection Interrupt (bit 5 of the Device Control Register) is 1, an interrupt is generated and appears on IRQ. Also, if SDN_DEB goes “true” and SDN Detection Control (bit 7 of the Device Control Register) is 0, the Automatic Shutdown sequence begins for SIM2 only, leaving SIM1 unaffected.




Figure 2. BSI Debounce Timing – SIM1 Active and SIM2 Isolated

Notes:

- BSI debounce count value set to 4
- SIM1 Active, SIM2 powered but Isolated
- BSI Detection Control set to 0
- Battery Removal Interrupt set to 1

SCES830A –MAY 2012–REVISED AUGUST 2013

www.ti.com

Once BSI is high for four cycles, BSI_DEB goes high causing automatic shutdown sequence on both SIMs. Since SIM1 is active with SIMCLK running, it follows the staged shutdown sequence. Since SIM2 is powered up but inactive, it follows the instant shutdown sequence.




Figure 3. BSI Debounce Timing – SIM1 Clock Stop and SIM2 Isolated

Notes:

- BSI debounce counter set to 4
- SIM1 Active in Clock Stop Mode
- SIM2 powered but Isolated
- BSI Detection Control set to 0
- Battery Removal Interrupt set to 1

Once BSI is high for four cycles, BSI_DEB goes high causing automatic shutdown sequence on both SIMs. Since SIM1 is active with SIMCLK stopped, it follows the instant shutdown sequence. Since SIM2 is powered up but inactive, it follows the instant shutdown sequence.




Figure 4. BSI Debounce Timing – SIM1 Isolated, SIM2 Active

Notes:

BSI debounce counter set to 4

SIM2 Active

SIM1 powered but Isolated

BSI Detection Control set to 0

Battery Removal Interrupt set to 1

Once BSI is high for four cycles, BSI_DEB goes high causing automatic shutdown sequence on both SIMs. Since SIM2 is active with SIMCLK running, it follows the staged shutdown sequence. Since SIM1 is powered up but inactive, it follows the instant shutdown sequence.




Figure 5. BSI Debounce Timing – Debounce Count Value Write During Debounce

Notes:

BSI debounce count value set to 4, but written to 7 during debounce

SIM1 Active

SIM2 powered but Isolated

BSI Detection Control set to 0

Battery Removal Interrupt set to

BSI_DEB goes high causing automatic shutdown sequence on both SIM's. Since SIM1 follows the staged shutdown sequence. SIM2 follows the instant shutdown sequence. BSI returning low does not interrupt shutdown sequence.




Figure 6. SDN Debounce Timing – SDN Detection Level High

Notes:

- SDN debounce count value set to 4
- SIM1 Active
- SIM2 powered but Isolated
- SDN Detection Control set to 0
- SDN Detection level set to 1
- SDN Detection Interrupt set to 1

Once SDN is high for four cycles, SDN_DEB goes high causing automatic shutdown sequence on SIM2. SIM1 is unaffected. Since SIM2 is powered up but inactive, it follows the instant shutdown sequence.




Figure 7. SDN Debounce Timing – SDN Detection Level Low

Notes:

SDN debounce count value set to 4

SIM1 Active

SIM2 powered but Isolated

SDN Detection Control set to 0

SDN Detection level set to 0

SDN Detection Interrupt set to 1

Once SDN is low for four cycles, SDN_DEB goes low causing automatic shutdown sequence on SIM2. SIM1 is unaffected. Since SIM2 is powered up but inactive, it follows the instant shutdown sequence.




Figure 8. SDN Debounce Timing – SIM1 Isolated and SIM 2 Active

Notes:

SDN debounce count value set to 4

SIM1 powered but Isolated

SIM2 Active

SDN Detection Control set to 0

SDN Detection level set to 1

SDN Detection Interrupt set to 1

SDN_DEB goes high causing automatic shutdown sequence on SIM2. Since SIM2 is active with SIMCLK running, it follows the staged shutdown sequence, SIM1 is unaffected.

ABSOLUTE MAXIMUM RATINGS

over operating free-air temperature range (unless otherwise noted)

Level Translator⁽¹⁾

| | | | MIN | MAX | UNIT |
|------------------|--|---|------|------|------|
| VDDIO | Supply voltage range | | –0.3 | 4.0 | V |
| V _I | Input voltage range | VDDIO-port | –0.5 | 4.6 | V |
| | | VSIMx-port | –0.5 | 4.6 | |
| | | Control inputs | –0.5 | 4.6 | |
| V _O | Voltage range applied to any output in the high-impedance or power-off state | VDDIO-port | –0.5 | 4.6 | V |
| | | VSIMx-port | –0.5 | 4.6 | |
| V _O | Voltage range applied to any output in the high or low state | VDDIO-port | –0.5 | 4.6 | V |
| | | VSIMx-port | –0.5 | 4.6 | |
| I _{IK} | Input clamp current | V _I < 0 | | –50 | mA |
| I _{OK} | Output clamp current | V _O < 0 | | –50 | mA |
| I _O | Continuous output current | | | ±50 | mA |
| | Continuous current through V _{CCA} or GND | | | ±100 | mA |
| T _{stg} | Storage temperature range | | –65 | 150 | °C |
| ESD rating | Human-Body Model (HBM) | All pins | | 2.5 | kV |
| | Human-Body Model (HBM-HV) | Baseband Side I/O: SIM1CLK, SIM1I/O, SIM1RST, SIM2CLK, SIM2I/O, SIM2RST | | 6 | Kv |
| | Charge-Device Model (CDM) | | | 1000 | V |

- (1) Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

LDO⁽¹⁾

| | | | MIN | MAX | UNIT |
|------------------|----------------------------|--------------------------|------|------|------|
| V _{IN} | Input voltage range | | –0.3 | 6 | V |
| V _{OUT} | Output voltage range | | –0.3 | 6 | V |
| T _J | Junction temperature range | | –55 | 150 | °C |
| T _{stg} | Storage temperature range | | –55 | 150 | °C |
| ESD rating | Human-Body Model (HBM-HV) | LDO Output: VSIM1, VSIM2 | | 6 | kV |
| | Charged-Device Model (CDM) | | | 1000 | V |

- (1) Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

THERMAL IMPEDANCE RATINGS

| | | | | UNIT |
|---------------|--|-------------|----|------|
| θ_{JA} | Package thermal impedance ⁽¹⁾ | RGE package | 45 | °C/W |

(1) The package thermal impedance is calculated in accordance with JESD 51-7.

RECOMMENDED OPERATING CONDITIONS⁽¹⁾

Level Translator

| | Description | MIN | MAX | UNIT |
|---------------------|------------------------------------|-------------|-------------|------|
| VDDIO | Supply voltage | 1.7 | 3.3 | V |
| V _{IH} | High-level input voltage | VDDIO × 0.7 | 1.9 | V |
| V _{IL} | Low-level input voltage | | | |
| $\Delta t/\Delta v$ | Input transition rise or fall rate | 0 | VDDIO × 0.3 | V |
| $\Delta t/\Delta v$ | Input transition rise or fall rate | | 5 | ns/V |
| T _A | Operating free-air temperature | –40 | 85 | °C |

(1) All unused data inputs of the device must be held at V_{CCI} or GND to ensure proper device operation. Refer to the TI application report, *Implications of Slow or Floating CMOS Inputs*, literature number SCBA004.

ELECTRICAL CHARACTERISTICS

Level Translator

over recommended operating free-air temperature range (unless otherwise noted)

| PARAMETER | | TEST CONDITIONS | VDDIO | VSIM1 | VSIM2 | MIN | TYP ⁽¹⁾ | MAX | UNIT |
|-----------------|----------------|--|-------------------|-------------------------------------|-------------------------------------|-------------|--------------------|-----|------|
| V _{OH} | SIM1_RST | I _{OH} = −100 μA Push-Pull | 1.7 V to 3.3 V | 1.8 V / 2.95 V (Supplied by LDO) | 1.8 V / 2.95 V (Supplied by LDO) | VSIM1 × 0.8 | | V | |
| | SIM1_CLK | VSIM1 × 0.8 | | | | | | | |
| | SIM1_I/O | I _{OH} = −10 μA Open-Drain | | | | VSIM1 × 0.8 | | | |
| | | I _{OH} = −100 μA Push-Pull | | | | | | | |
| | SIM2_RST | I _{OH} = −100 μA Push-Pull | | | | VSIM2 × 0.8 | | | |
| | SIM2_CLK | VSIM2 × 0.8 | | | | | | | |
| | SIM2_I/O | I _{OH} = −10 μA Open-Drain | | | | VSIM2 × 0.8 | | | |
| | | I _{OH} = −100 μA Push-Pull | | | | | | | |
| | SIM_I/O | I _{OH} = −10 μA Open-Drain | | | | VDDIO × 0.8 | | | |
| | | I _{OH} = −100 μA Push-Pull | | | | | | | |
| V _{OL} | SIM1_RST | I _{OL} = 1 mA Push-Pull | 1.7 V to 3.3 V | 1.8 V / 2.95 V (Supplied by LDO) | 1.8 V / 2.95 V (Supplied by LDO) | VSIM1 × 0.2 | | V | |
| | SIM1_CLK | I _{OL} = 1 mA Push-Pull | | | | VSIM1 × 0.2 | | | |
| | SIM1_I/O | I _{OL} = 1 mA Open-Drain | | | | 0.3 | | | |
| | | I _{OL} = 1 mA Push-Pull | | | | | | | |
| | SIM2_RST | I _{OL} = 1 mA Push-Pull | | | | VSIM2 × 0.2 | | | |
| | SIM2_CLK | I _{OL} = 1 mA Push-Pull | | | | VSIM2 × 0.2 | | | |
| | SIM2_I/O | I _{OL} = 1 mA Open-Drain | | | | 0.3 | | | |
| | | I _{OL} = 1 mA Push-Pull | | | | | | | |
| | SIM_I/O | I _{OL} = 1 mA Open-Drain | | | | 0.3 | | | |
| | | I _{OL} = 1 mA Push-Pull | | | | | | | |
| I _I | Control inputs | V _I = OE | 1.7 V to 3.3 V | 1.8 V / 2.95 V (Supplied by LDO) | 1.8 V / 2.95 V (Supplied by LDO) | ±1 | | μA | |
| C _{io} | SIM_I/O port | | | | | 7 | | pF | |
| | SIMx port | | | | | 4 | | | |
| C _i | Control inputs | V _I = VDDIO or GND | | | | 3 | | pF | |
| | Clock input | | | | | | | | |

(1) All typical values are at T_A = 25°C.

ELECTRICAL CHARACTERISTICS

LDO (Control Input Logic = High)

over operating free-air temperature range (unless otherwise noted)

| PARAMETER | | TEST CONDITIONS | | MIN | TYP ⁽¹⁾ | MAX | UNIT |
|----------------------|--------------------------------|--|------------|------|--------------------|------|------|
| V _{BAT} | Input voltage | | | 2.3 | | 5.5 | V |
| V _{OUT} | Output voltage | Class-B Mode | | 2.85 | 2.95 | 3.05 | V |
| | | Class-C Mode | | 1.7 | 1.8 | 1.9 | |
| V _{DO} | Dropout voltage | I _{OUT} = 50 mA | | | | 100 | mV |
| I _{GND} | Ground-pin current | I _{OUT} = 0 mA | | | | 35 | μA |
| | | I _{OUT} = 50 mA | | | | 150 | |
| I _{OUT(SC)} | Short-circuit current | R _L = 0 Ω | | | | 400 | mA |
| C _{OUT} | Output Capacitor | | | | 1 | | μF |
| PSRR | Power-supply rejection ratio | V _{BAT} = 3.25 V, V _{SIMx} = 1.8 V or 3 V, C _{OUT} = 1 μF, I _{OUT} = 50 mA | f = 1 kHz | 50 | | | dB |
| | | | f = 10 kHz | 40 | | | |
| T _{STR} | Start-up time | V _{SIMx} = 1.8 V or 3 V, I _{OUT} = 10 mA, C _{OUT} = 1 μF | | | | 50 | μS |
| T _J | Operating junction temperature | | | | −40 | 85 | °C |

(1) All typical values are at T_A = 25°C.

GENERAL ELECTRICAL CHARACTERISTICS

over operating free-air temperature range (unless otherwise noted)

| Operating with an temperature range (unless otherwise noted) | | | | | | |
|--|--|---|------|-----|------|------|
| PARAMETER | | TEST CONDITIONS | MIN | TYP | MAX | UNIT |
| I _{BAT_ACT} | VBAT Current Consumption in Active Mode | RSTX = High, VSIMx = 1.8 V or 2.95 V, I _{OUT} = 0 mA VBAT = 2.3 to 5.5 V VDDIO = 1.7 to 3.3 V | | | 250 | μA |
| I _{BAT_SDN} | VBAT Current Consumption in Shutdown Mode | RSTX = Low, VSIMx = 0 V (Disabled), I _{OUT} = 0 mA VBAT = 2.3 to 5.5 V VDDIO = 1.8 V | | 1 | 5 | |
| I _{DDIO_ACT} | VDDIO Current Consumption in Active Mode | RSTX = High, VSIMx = 1.8 V or 2.95 V, I _{OUT} = 0 mA VBAT = 2.3 to 5.5 V VDDIO = 1.7 to 3.3 V | | | 5 | |
| I _{DDIO_SDN} | VDDIO Current Consumption in Shutdown Mode | RSTX = Low, VSIMx = 0 V (Disabled), I _{OUT} = 0 mA VBAT = 2.3 to 5.5 V VDDIO = 1.7 to 3.3 V | | | 0.25 | |
| BSI _{Threshold} | Comparator Threshold | BSI detection level “1” | 1.6 | | 1.7 | V |
| | | BSI detection level “0” | 1.1 | | 1.3 | |
| Hyst | Internal hysteresis of comparator | | | ±50 | | mV |
| CLK _{Int} | Internal System Clock | | –20% | 32 | +20% | KHz |
| R _{SIMPU} | SIM I/O pull-up | | 18 | 20 | 22.6 | kΩ |
| R _{SIMxPU} | SIMx I/O pull-up | Class B | 6 | 7.5 | 9 | kΩ |
| | | Class C | 3.8 | 4.5 | 5.2 | |
| R _{SIMPD} | SIMx I/O pull-down | Active pull-downs are connected to the VSIM1/2 regulator output to the SIM1/2 CLK, SIM1/2 RST, SIM1/2 I/O when the respective regulator is disabled | | | 2 | kΩ |

SWITCHING CHARACTERISTICS

VSIMx = 1.8 V or 2.95 V Supplied by Internal LDO, VBAT = 2.3V to 5.5V

over recommended operating free-air temperature range (unless otherwise noted)

| PARAMETER | | TEST CONDITIONS | VDDIO = 1.7 V to 3.3 V | | UNIT |
|---------------------------------------|---------------------|-----------------|------------------------|------|------|
| | | | MIN | MAX | |
| t_{rA} Baseband side to SIM side | SIMx_I/O | Open Drain | | 320 | ns |
| | SIMx_I/O | Push Pull | | 8.6 | ns |
| | SIMx_RST | Push Pull | | 4.3 | ns |
| | SIMx_CLK | Push Pull | | 9.3 | ns |
| t_{fA} Baseband side to SIM side | SIMx_I/O | Open Drain | | 16 | ns |
| | SIMx_I/O | Push Pull | | 6.5 | ns |
| | SIMx_RST | Push Pull | | 4.5 | ns |
| | SIMx_CLK | Push Pull | | 9.5 | ns |
| t_{rB} SIM side to Baseband side | SIM_I/O | Open Drain | | 245 | ns |
| | SIM_I/O | Push Pull | | 10 | ns |
| t_{fB} SIM side to Baseband side | SIM_I/O | Open Drain | | 18 | ns |
| | SIM_I/O | Push Pull | | 8 | ns |
| f_{max} | SIMx_CLK | Push Pull | | 5 | MHz |
| t_{PLH} | SIM_CLK to SIMx_CLK | Push Pull | | 8.9 | ns |
| | SIM_RST to SIMx_RST | Push Pull | | 8 | ns |
| | SIM_IO to SIMx_IO | Open Drain | | 18 | ns |
| | SIM_IO to SIMx_IO | Push Pull | | 10 | ns |
| | SIMx_IO to SIMIO | Open Drain | | 10 | ns |
| | SIMx_IO to SIMIO | Push Pull | | 10.5 | ns |
| t_{PHL} | SIM_CLK to SIMx_CLK | Push Pull | | 10 | ns |
| | SIM_RST to SIMx_RST | Push Pull | | 7 | ns |
| | SIM_IO to SIMx_IO | Open Drain | | 23 | ns |
| | SIM_IO to SIMx_IO | Push Pull | | 8 | ns |
| | SIMx_IO to SIM_IO | Open Drain | | 23 | ns |
| | SIMx_IO to SIM_IO | Push Pull | | 10 | ns |

OPERATING CHARACTERISTICS

$T_A = 25^\circ\text{C}$, $V_{SIMx} = 1.8\text{ V}$ for Class C, $V_{SIMx} = 2.95\text{ V}$ for Class B

| PARAMETER | | TEST CONDITIONS | TYP | UNIT |
|----------------|---------|--|-----|------|
| $C_{pd}^{(1)}$ | Class B | $C_L = 0$, $f = 5\text{ MHz}$, $t_r = t_f = 1\text{ ns}$ | 11 | pF |
| | Class C | | 9.5 | |

(1) Power dissipation capacitance per transceiver

APPLICATION INFORMATION

The LDO's included on the TXS02326A achieve ultra-wide bandwidth and high loop gain, resulting in extremely high PSRR at very low headroom ($V_{BAT} - V_{SIM1/2}$). The TXS02326A provides fixed regulation at 1.8V or 2.95V. Low noise, enable through I²C control, and low ground pin current make it ideal for portable applications. The device offers sub-bandgap output voltages, current limit, thermal protection, and is fully specified from –40°C to +85°C.




Figure 9. Typical Application circuit for TXS02326A

Input and Output Capacitor Requirements

It is good analog design practice to connect a 1.0 µF low equivalent series resistance (ESR) capacitor across the input supply (VBAT) near the regulator. Also, a 0.1µF is required for the logic core supply (VDDIO).

This capacitor will counteract reactive input sources and improve transient response, noise rejection, and ripple rejection. A higher-value capacitor may be necessary if large, fast rise-time load transients are anticipated or if the device is located several inches from the power source. The LDO's are designed to be stable with standard ceramic capacitors of values 1.0 µF or larger. X5R- and X7R-type capacitors are best because they have minimal variation in value and ESR over temperature. Maximum ESR should be < 1.0 Ω.

Output Noise

In most LDO's, the bandgap is the dominant noise source. To improve ac performance such as PSRR, output noise, and transient response, it is recommended that the board be designed with separate ground planes for V_{IN} and V_{OUT} , with each ground plane connected only at the GND pin of the device. In addition, the ground connection for the bypass capacitor should connect directly to the GND pin of the device.

Internal Current Limit

The TXS02326A internal current limit helps protect the regulator during fault conditions. During current limit, the output sources a fixed amount of current that is largely independent of output voltage. For reliable operation, the device should not be operated in a current limit state for extended periods of time.

The PMOS pass element in the TXS02326A has a built-in body diode that conducts current when the voltage at $V_{SIM1/2}$ exceeds the voltage at V_{BAT} . This current is not limited, so if extended reverse voltage operation is anticipated, external limiting may be appropriate.

Dropout Voltage

The TXS02326A uses a PMOS pass transistor to achieve low dropout. When ($V_{BAT} - V_{SIM1/2}$) is less than the dropout voltage (V_{DO}), the PMOS pass device is in its linear region of operation and the input-to-output resistance is the $R_{DS(ON)}$ of the PMOS pass element. V_{DO} will approximately scale with output current because the PMOS device behaves like a resistor in dropout.

Startup

The TXS02326A uses a quick-start circuit which allows the combination of very low output noise and fast start-up times. Note that for fastest startup, V_{BATT} should be applied first, and then enabled by asserting the I²C register.

Transient Response

As with any regulator, increasing the size of the output capacitor reduces over/undershoot magnitude but increases duration of the transient response.

Minimum Load

The TXS02326A is stable and well-behaved with no output load. Traditional PMOS LDO regulators suffer from lower loop gain at very light output loads. The TXS02326A employs an innovative low-current mode circuit to increase loop gain under very light or no-load conditions, resulting in improved output voltage regulation performance down to zero output current.

THERMAL INFORMATION



Thermal Protection

Thermal protection disables the output when the junction temperature rises to approximately +160°C, allowing the device to cool. When the junction temperature cools to approximately +140°C the output circuitry is again enabled. Depending on power dissipation, thermal resistance, and ambient temperature, the thermal protection circuit may cycle on and off. This cycling limits the dissipation of the regulator, protecting it from damage because of overheating.

Any tendency to activate the thermal protection circuit indicates excessive power dissipation or an inadequate heat sink. For reliable operation, junction temperature should be limited to +85°C maximum. To estimate the margin of safety in a complete design (including heat sink), increase the ambient temperature until the thermal protection is triggered; use worst-case loads and signal conditions. For good reliability, thermal protection should trigger at least +35°C above the maximum expected ambient condition of your particular application. This configuration produces a worst-case junction temperature of +85°C at the highest expected ambient temperature and worst-case load.

The internal protection circuitry of the TXS02326A has been designed to protect against overload conditions. It was not intended to replace proper heat sinking. Continuously running the TXS02326A into thermal shutdown will degrade device reliability.

TYPICAL CHARACTERISTICS



TYPICAL CHARACTERISTICS (continued)




Figure 12. Output Voltage vs Temperature, Class-B/C




Figure 13. Load Regulation, $I_{OUT} = 50$ mA, Class-C




Figure 14. Load Regulation, $I_{OUT} = 50$ mA, Class-B




Figure 15. Line Regulation, $I_{OUT} = 50$ mA, Class-C

SCES830A –MAY 2012–REVISED AUGUST 2013

www.ti.com

TYPICAL CHARACTERISTICS (continued)




Figure 16. Line Regulation, Iout = 50 mA, Class-B




Figure 17. Current Limit vs Input Voltage, Class-B/C




Figure 18. Ground Current vs Temperature, Class-C

REVISION HISTORY

| Changes from Original (May 2012) to Revision A | Page |
|---|------|
| <ul style="list-style-type: none"> Deleted I_{SHDN} from LDO characteristics as $I_{SHUTDOWN}$ applies to total device while in the reset mode outlined in the General Characteristics 21 Added I_{BAT_ACT}, I_{BAT_SDN}, I_{DDIO_ACT}, and I_{DDIO_SDN} to the General Electrical Characteristics table 21 | |



Distributor of Texas Instruments: Excellent Integrated System Limited

Datasheet of TXS02326AMRGER - IC SIM CARD MUX 2:1 24VQFN

Contact us: sales@integrated-circuit.com Website: www.integrated-circuit.com

PACKAGE OPTION ADDENDUM

www.ti.com

2-Aug-2013

PACKAGING INFORMATION

| Orderable Device | Status (1) | Package Type | Package Drawing | Pins | Package Qty | Eco Plan (2) | Lead/Ball Finish | MSL Peak Temp (3) | Op Temp (°C) | Device Marking (4/5) | Samples |
|------------------|---------------|--------------|--------------------|------|----------------|----------------------------|------------------|----------------------|--------------|-------------------------|-------------------------|
| TXS02326AMRGER | ACTIVE | VQFN | RGE | 24 | 3000 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-2-260C-1 YEAR | -40 to 85 | YJ326A | Samples |

(1) The marketing status values are defined as follows:

ACTIVE: Product device recommended for new designs.

LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

PREVIEW: Device has been announced but is not in production. Samples may or may not be available.

OBsolete: TI has discontinued the production of the device.

(2) Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS), Pb-Free (RoHS Exempt), or Green (RoHS & no Sb/Br) - please check <http://www.ti.com/productcontent> for the latest availability information and additional product content details.

TBD: The Pb-Free/Green conversion plan has not been defined.

Pb-Free (RoHS): TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.

Pb-Free (RoHS Exempt): This component has a RoHS exemption for either 1) lead-based flip-chip solder bumps used between the die and package, or 2) lead-based die adhesive used between the die and leadframe. The component is otherwise considered Pb-Free (RoHS compatible) as defined above.

Green (RoHS & no Sb/Br): TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight in homogeneous material)

(3) MSL, Peak Temp. -- The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

(4) There may be additional marking, which relates to the logo, the lot trace code information, or the environmental category on the device.

(5) Multiple Device Markings will be inside parentheses. Only one Device Marking contained in parentheses and separated by a "-" will appear on a device. If a line is indented then it is a continuation of the previous line and the two combined represent the entire Device Marking for that device.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

PACKAGE MATERIALS INFORMATION

TAPE AND REEL INFORMATION



*All dimensions are nominal

| Device | Package Type | Package Drawing | Pins | SPQ | Reel Diameter (mm) | Reel Width W1 (mm) | A0 (mm) | B0 (mm) | K0 (mm) | P1 (mm) | W (mm) | Pin1 Quadrant |
|----------------|--------------|-----------------|------|------|--------------------|--------------------|---------|---------|---------|---------|--------|---------------|
| TXS02326AMRGER | VQFN | RGE | 24 | 3000 | 330.0 | 12.4 | 4.25 | 4.25 | 1.15 | 8.0 | 12.0 | Q1 |

TAPE AND REEL BOX DIMENSIONS




*All dimensions are nominal

| Device | Package Type | Package Drawing | Pins | SPQ | Length (mm) | Width (mm) | Height (mm) |
|----------------|--------------|-----------------|------|------|-------------|------------|-------------|
| TXS02326AMRGER | VQFN | RGE | 24 | 3000 | 367.0 | 367.0 | 35.0 |

MECHANICAL DATA

RGE (S-PVQFN-N24)

PLASTIC QUAD FLATPACK NO-LEAD



4204104/G 07/11

- NOTES:
- A. All linear dimensions are in millimeters. Dimensioning and tolerancing per ASME Y14.5M-1994.
 - B. This drawing is subject to change without notice.
 - C. Quad Flatpack, No-Leads (QFN) package configuration.
 - D. The package thermal pad must be soldered to the board for thermal and mechanical performance.
 - E. See the additional figure in the Product Data Sheet for details regarding the exposed thermal pad features and dimensions.
 - F. Falls within JEDEC MO-220.

THERMAL PAD MECHANICAL DATA

RGE (S-PVQFN-N24)


PLASTIC QUAD FLATPACK NO-LEAD

THERMAL INFORMATION

This package incorporates an exposed thermal pad that is designed to be attached directly to an external heatsink. The thermal pad must be soldered directly to the printed circuit board (PCB). After soldering, the PCB can be used as a heatsink. In addition, through the use of thermal vias, the thermal pad can be attached directly to the appropriate copper plane shown in the electrical schematic for the device, or alternatively, can be attached to a special heatsink structure designed into the PCB. This design optimizes the heat transfer from the integrated circuit (IC).

For information on the Quad Flatpack No-Lead (QFN) package and its advantages, refer to Application Report, QFN/SON PCB Attachment, Texas Instruments Literature No. SLUA271. This document is available at www.ti.com.

The exposed thermal pad dimensions for this package are shown in the following illustration.




4206344-3/AK 08/15

NOTES: A. All linear dimensions are in millimeters

LAND PATTERN DATA

RGE (S-PVQFN-N24)

PLASTIC QUAD FLATPACK NO-LEAD



- NOTES:
- All linear dimensions are in millimeters.
 - This drawing is subject to change without notice.
 - Publication IPC-7351 is recommended for alternate designs.
 - This package is designed to be soldered to a thermal pad on the board. Refer to Application Note, Quad Flat-Pack Packages, Texas Instruments Literature No. SLUA271, and also the Product Data Sheets for specific thermal information, via requirements, and recommended board layout. These documents are available at www.ti.com <<http://www.ti.com>>.
 - Laser cutting apertures with trapezoidal walls and also rounding corners will offer better paste release. Customers should contact their board assembly site for stencil design recommendations. Refer to IPC 7525 for stencil design considerations.
 - Customers should contact their board fabrication site for recommended solder mask tolerances and via tenting recommendations for vias placed in the thermal pad.

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have **not** been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.

Products

| | |
|------------------------------|--|
| Audio | www.ti.com/audio |
| Amplifiers | amplifier.ti.com |
| Data Converters | dataconverter.ti.com |
| DLP® Products | www.dlp.com |
| DSP | dsp.ti.com |
| Clocks and Timers | www.ti.com/clocks |
| Interface | interface.ti.com |
| Logic | logic.ti.com |
| Power Mgmt | power.ti.com |
| Microcontrollers | microcontroller.ti.com |
| RFID | www.ti-rfid.com |
| OMAP Applications Processors | www.ti.com/omap |
| Wireless Connectivity | www.ti.com/wirelessconnectivity |

Applications

| | |
|-------------------------------|--|
| Automotive and Transportation | www.ti.com/automotive |
| Communications and Telecom | www.ti.com/communications |
| Computers and Peripherals | www.ti.com/computers |
| Consumer Electronics | www.ti.com/consumer-apps |
| Energy and Lighting | www.ti.com/energy |
| Industrial | www.ti.com/industrial |
| Medical | www.ti.com/medical |
| Security | www.ti.com/security |
| Space, Avionics and Defense | www.ti.com/space-avionics-defense |
| Video and Imaging | www.ti.com/video |

TI E2E Community

e2e.ti.com