

Excellent Integrated System Limited

Stocking Distributor

Click to view price, real time Inventory, Delivery & Lifecycle Information:

[Tripp Lite](#)
[TRAVELERC6](#)

For any questions, you can email us directly:

sales@integrated-circuit.com



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

Protect It! 2-Connector (C6, 3-Prong) In-Line Surge Protector, 306 Joules, Tel/Ethernet Protection

MODEL NUMBER: TRAVELERC6



Highlights

- 120V / 240V compatible
- 306 joule
- Two 3-prong (C6) connectors
- 1 in/1 out tel/modem/ethernet combo In-line design
- \$50,000 Ultimate Lifetime Insurance (U.S., Canada, and Puerto Rico only)

Package Includes

- TRAVELERC6 surge suppressor
- Instruction manual with warranty information

Description

Tripp Lite's Traveler In-Line surge suppressor features a 306 joule rating to handle even the strongest surges. In-line design, over current protection and 120/240V compatibility make this surge suppressor ideal for notebook computers and PDAs. Integrated phone line protection allows you to safeguard tel/modem and AC connections with a single unit. "Protected" LED lets you instantly know whether your wall jacks have potentially damaging signals. \$50,000 Ultimate Lifetime Insurance (U.S., Canada, and Puerto Rico only).

Features

- In-line design places AC line surge protection between your notebook computer or PDAs' power adapter and the power cord leading to the wall outlet
- 120/240V compatibility operates on voltage worldwide, automatically switching between 120V or 240V AC power
- Surge suppression rating: 306 joules
- Includes two 3-prong (C6) connectors
- Built-in LED confirms suppressor "protection present" (green)
- 1 line in/ 1 line out tel/modem/ethernet combo
- Single small push-button switch activates overcurrent detection circuit
- \$50,000 Ultimate Lifetime Insurance (U.S., Canada, and Puerto Rico only) covers connected equipment
- Automatic shutoff cuts power to outlets when the protection circuit has been compromised

Specifications

OUTPUT	
Frequency Compatibility	50 / 60 Hz
Output Receptacles	(2) C6 3-prong
Right-Angle Outlets	No



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

INPUT	
Nominal Input Voltage(s) Supported	120V AC; 230V AC
Recommended Electrical Service	120V (110-125V), 230V (220-250V)
Input Connection Type	Two 3-prong (C6) connectors
Input Cord Length (ft.)	0
Input Cord Length (m)	0.00
Input Cord Length Details	In-line
Voltage Compatibility (VAC)	120; 230
Maximum Surge Amps	12000
Right-Angle Plug	No
USER INTERFACE, ALERTS & CONTROLS	
Switches	Single small push-button switch activates over-current detection circuit
Diagnostic LED Details	Built-in LED confirms suppressor "protection present" (green)
SURGE / NOISE SUPPRESSION	
AC Suppression Joule Rating	306
AC Suppression Response Time	< 1 ns
Clamping Voltage (RMS)	150
UL1449 Let Through Rating	900V
DATALINE SURGE SUPPRESSION	
Telephone/DSL Protection	Yes
Telephone/DSL Protection Details	1 line
Cable (Coax) Protection	No
Network (Ethernet) Protection	Yes
PHYSICAL	
Shipping Dimensions (hwd / in.)	9 x 7 x 1.2
Shipping Dimensions (hwd / cm)	22.9 x 17.8 x 3
Unit Dimensions (hwd / in.)	1.75 x 4.25 x 1
Unit Dimensions (hwd / cm)	4.4 x 10.8 x 2.5
Unit Weight (lbs.)	0.2
Unit Weight (kg)	0.1
Material of Construction	Plastic



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

Form Factors Supported	In-line
CERTIFICATIONS	
UL1449 3rd Edition (AC Suppression)	UL1449 3rd Edition
UL497A (Communications)	UL497A
FCC Part 68 (Communications)	FCC Part 68
cUL / CSA (Canada)	cUL
Approvals	UL1950
WARRANTY	
Product Warranty Period (Worldwide)	Lifetime limited warranty

© 2016 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: <http://www.tripplite.com/products/product-certification-agencies>