Excellent Integrated System Limited

Stocking Distributor

Click to view price, real time Inventory, Delivery & Lifecycle Information:

Pomona Electronics 3837

For any questions, you can email us directly: sales@integrated-circuit.com




Distributor of Pomona Electronics: Excellent Integrated System Limited

Datasheet of 3837 - ADT BNC FLE 2 CONDUCT 3.5MM PLUG

Contact us: sales@integrated-circuit.com Website: www.integrated-circuit.com

Pomona®

Model 3837 Adapter BNC Female To Tini-Plug



FEATURES:

- Permits BNC male to be used with equipment having tini jacks.
- Readily adapts equipment to available BNC coaxial cables.
- All metal construction to insure proper shielding.

MATERIALS:

Upper Conn: BNC Female

Body and Fittings: Tarnish resistant.

Center Contact: Gold plated per requirements of MIL-C-39012.

Adapter Body:

Material: Brass per QQ-B-626, Alloy 360, ½ Hard.

Finish: Nickel plated per QQ-N-290, Class 2, 200/300 microinches.

Marking: "POMONA ELECTRONICS MODEL 3837."

Lower Conn: Tini Plug

RATINGS:

Operating Temperature: -55° C. to $+125^{\circ}$ C. $(-67^{\circ}$ F. to $+257^{\circ}$ F.)

Operating Voltage: 500 VRMS.

ORDERING INFORMATION: Model 3837

All dimensions are in inches. Tolerances (except noted): $.xx = \pm .02$ " (,51 mm), $.xxx = \pm .005$ " (,127 mm). All specifications are to the latest revisions. Specifications are subject to change without notice. Registered trademarks are the property of their respective companies. Made in USA

6/9/99 Sales: 800-490-2361 Fax: 888-403-3360
SY/EH/LS Technical Assistance: 800-241-2060
S\Engineering\Release\DataSheet\FlukeDataSheet\d3837_1_01.doc

Pomona*ACCESS* **90586** (800) 444-6785 or (425) 446-6010 More drawings available at www.pomonaelectronics.com

Page 1 of 1