

## Excellent Integrated System Limited

Stocking Distributor

Click to view price, real time Inventory, Delivery & Lifecycle Information:

[Molex Connector Corporation](#)  
[0625002992](#)

For any questions, you can email us directly:

[sales@integrated-circuit.com](mailto:sales@integrated-circuit.com)

## Step-Up Transformer

### Step-Up Transformer For TM-3000 and TM-4000 Presses

**molex**

### Application Tooling Specification Sheet



Order No. 62500-2992

## FEATURES

- Allows 240V presses to be operated on standard 115V power.
- Input is circuit-breaker protected.
- 50Hz or 60Hz operation (does not change line frequency)
- Input is a standard 3-wire grounded plug (NEMA5-15P) with a 5 ft. (1.5m) cord.
- Output is a standard 3-wire grounded receptacle (NEMA6-15R) that is compatible with the press cord.

## SCOPE

The step-up transformer is intended for use with the 240V version of the Molex TM-3000 press and the TM-4000 press (order numbers 63801-7300 and 63801-7600).



**Do not use this transformer with the 120V TM-3000 (order number 63801-7200) or any other press.**

## Installation

1. Place the transformer on a surface capable of supporting at least 20 lbs. (9 kg) and with adequate ventilation.



**WARNING: This transformer may become hot. Keep it away from combustible items and avoid touching it while in use.**

2. Connect the output receptacle of the transformer to the US cord (NEMA6-15P plug) supplied with the press.
3. Connect the input plug of the transformer to a GROUNDED 115VAC receptacle.
4. Turn on the press power.
5. If the press does not power-up, reset the circuit breaker on the transformer and/or check the fuse in the press.



Visit our Web site at <http://www.molex.com>