## **Excellent Integrated System Limited**

Stocking Distributor

Click to view price, real time Inventory, Delivery & Lifecycle Information:

Micro Commercial Components (MCC)

DTC144EE-TP

For any questions, you can email us directly: <a href="mailto:sales@integrated-circuit.com">sales@integrated-circuit.com</a>



Datasheet of DTC144EE-TP - TRANS PREBIAS NPN 150MW SOT523 Contact us: sales@integrated-circuit.com Website: www.integrated-circuit.com



**Micro Commercial Components** 

Pb

Micro Commercial Components 20736 Marilla Street Chatsworth CA 91311

Phone: (818) 701-4933 Fax: (818) 701-4939

## DTC144EE

### **Features**

- Lead Free Finish/RoHS Compliant ("P" Suffix designates RoHS Compliant. See ordering information)
- Epoxy meets UL 94 V-0 flammability rating
- Moisure Sensitivity Level 1
- Built-in bias resistors enable the configuration of an inverter circuit without connecting external input resistors
- The bias resistors consist of thin-film resistors with complete isolation to allow negative biasing of the input. They also have the advantage of almost completely eliminating parasitic effects.
- Only the on/off conditions need to be set for operation, making device design easy

device design easy
 Halogen free available upon request by adding suffix "-HF"


Absolute maximum ratings @  $25^{\circ}$ 

Symbol	Parameter		Тур	Max	Unit
V <sub>cc</sub>	Supply voltage		50		V
$V_{IN}$	Input voltage	-10		40	V
Ιo	Output current		100		mA
$P_d$	Power dissipation		150		mW
$T_j$	Junction temperature		150		$^{\circ}$
T <sub>stg</sub>	Storage temperature	-55		150	$^{\circ}$

### Electrical Characteristics @ 25°C


Symbol	Parameter		Тур	Max	Unit
$V_{I(off)}$	Input voltage (V <sub>CC</sub> =5V, I <sub>O</sub> =100 μ A)			0.5	V
$V_{I(on)}$	$(V_0=0.3V, I_0=2mA)$	3.0			V
$V_{O(on)}$	Output voltage (I <sub>O</sub> /I <sub>I</sub> =10mA/0.5mA)			0.3	V
$I_{l}$	Input current (V <sub>I</sub> =5V)			0.18	mA
I <sub>O(off)</sub>	Output current (V <sub>CC</sub> =50V, V <sub>I</sub> =0)			0.5	μA
Gı	DC current gain (V <sub>0</sub> =5V, I <sub>0</sub> =5mA)	68			
$R_1$	Input resistance	32.9	47	61.1	KΩ
$R_2/R_1$	Resistance ratio	0.8	1.0	1.2	
f <sub>T</sub>	Transition frequency ( $V_{CE}$ =10V, $I_E$ =5mA, f=100MHz)		250		MHz


#### ●Equivalent circuit



\*Marking: 26

# NPN Digital Transistors





	DIMENSIONS					
		INCHES MM				
DIM	MIN	MAX	MIN	MAX	NOTE	
Α	.059	.067	1.50	1.70		
В	.030	.033	0.75	0.85		
С	.057	.069	1.45	1.75		
D	.020 Nominal		0.50Nominal			
Е	.035	.043	0.90	1.10		
G	.000	.004	.000	.100		
Н	.028	.031	.70	0.80		
J	.004	.008	.100	.200		
K	.010	.014	.25	.35		



## DTC144EE



#### Electrical characteristic curves




Fig.1 Input voltage vs. output current (ON characteristics)




Fig.2 Output current vs. input voltage (OFF characteristics)




Fig.3 DC current gain vs. output current




Fig.4 Output voltage vs. output current

## Distributor of Micro Commercial Components (MCC): Excellent Integrated System Limite

Datasheet of DTC144EE-TP - TRANS PREBIAS NPN 150MW SOT523

Contact us: sales@integrated-circuit.com Website: www.integrated-circuit.com



# Ordering Information :

Device	Packing
Part Number-TP	Tape&Reel 3Kpcs/Reel

Note: Adding "-HF" suffix for halogen free, eg. Part Number-TP-HF

#### \*\*\*IMPORTANT NOTICE\*\*\*

**Micro Commercial Components Corp.** reserves the right to make changes without further notice to any product herein to make corrections, modifications, enhancements, improvements, or other changes. **Micro Commercial Components Corp.** does not assume any liability arising out of the application or use of any product described herein; neither does it convey any license under its patent rights, nor the rights of others. The user of products in such applications shall assume all risks of such use and will agree to hold **Micro Commercial Components Corp.** and all the companies whose products are represented on our website, harmless against all damages.

#### \*\*\*LIFE SUPPORT\*\*\*

MCC's products are not authorized for use as critical components in life support devices or systems without the express written approval of Micro Commercial Components Corporation.

#### \*\*\*CUSTOMER AWARENESS\*\*\*

Counterfeiting of semiconductor parts is a growing problem in the industry. Micro Commercial Components (MCC) is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. MCC strongly encourages customers to purchase MCC parts either directly from MCC or from Authorized MCC Distributors who are listed by country on our web page cited below. Products customers buy either from MCC directly or from Authorized MCC Distributors are genuine parts, have full traceability, meet MCC's quality standards for handling and storage. MCC will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. MCC is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.

Revision: B 3 of 3 2013/01/01